



## 1-5/8" RADIAFLEX® RLKU Cable, A-series

- RADIAFLEX® functions as a distributed antenna to provide communications in tunnels, mines and large building complexes and is the solution for any application in confined areas.
- Slots in the copper outer conductor allow a controlled portion of the internal RF energy to be radiated into the surrounding environment. Conversely, a signal transmitted near the cable will couple into the slots and be carried along the cable length.
- RADIAFLEX® is used for both one-way and two-way communication systems and because of its broadband capability, a single radiating cable can handle multiple communication systems simultaneously.
- This RADIAFLEX® radiating cable utilize a low-loss cellular polyethylene foam dielectric and a smooth copper outer conductor which offers a superior electrical performance together with good bending properties.



RLK cable, A-series

### FEATURES / BENEFITS

- ➔ Ultra wideband from 30 MHz to 2700 MHz
- ➔ For applications in tunnels and buildings
- ➔ Low coupling loss variations
- ➔ Lowest insertion loss and excellent coupling performance to minimize count of active equipment
- ➔ Best-in-class, RF ultra wideband radiating cable, accommodating all current and future commercial radio and private radio service from 30 MHz to 2700 MHz

### Technical Features

#### GENERAL SPECIFICATIONS

|      |  |        |
|------|--|--------|
| Size |  | 1-5/8" |
|------|--|--------|

#### ELECTRICAL SPECIFICATIONS

|                               |                 |              |
|-------------------------------|-----------------|--------------|
| Max. Operating Frequency      | MHz             | 2700         |
| Cable Type                    |                 | RLKU         |
| Impedance                     | Ohm             | 50 +/- 2     |
| Velocity                      | %               | 89           |
| Capacitance                   | pF/m (pF/ft)    | 76 (23.2)    |
| Inductance                    | µH/m (µH/ft)    | 0.19 (0.058) |
| DC-resistance inner conductor | Ω/km (Ω/1000ft) | 1.62 (0.49)  |
| DC-resistance outer conductor | Ω/km (Ω/1000ft) | 1.47 (0.45)  |
| Stop bands                    | MHz             | 540-610      |

#### MECHANICAL SPECIFICATIONS

|                                     |              |  |
|-------------------------------------|--------------|--|
| Jacket                              |              | JFN  |
| Jacket Description                  |              | Halogen free, non corrosive, flame and fire retardant, low smoke, polyolefin |
| Slot Design                         |              | Groups of vertical slots at short intervals                                  |
| Inner Conductor Material            |              | Corrugated Copper Tube   |
| Outer Conductor Material            |              | Overlapping Copper Foil  |
| Diameter Inner Conductor            | mm (in)      | 17.6 (0.69)  |
| Diameter Outer Conductor            | mm (in)      | 44.2 (1.74)  |
| Diameter over Jacket                | mm (in)      | 48.2 (1.9)   |
| Minimum Bending Radius, Single Bend | mm (in)      | 700 (28)   |
| Cable Weight                        | kg/m (lb/ft) | 1 (0.68)   |
| Tensile Force                       | N (lb)       | 1200 (270)   |
| Indication of Slot Alignment        |              | Guides opposite to slots   |
| Recommended Clamp Spacing           | m (ft)       | 1.5 (5)  |
| Minimum Distance to Wall            | mm (in)      | 80 (3.15)  |

#### TEMPERATURE SPECIFICATIONS

|                          |        |                         |
|--------------------------|--------|-------------------------|
| Storage Temperature      | °C(°F) | -70 to 85 (-94 to 185 ) |
| Installation Temperature | °C(°F) | -25 to 60 (-13 to 140 ) |
| Operation Temperature    | °C(°F) | -40 to 85 (-40 to 185 ) |



## 1-5/8" RADIAFLEX® RLKU Cable, A-series

### ATTENUATION AND POWER RATING

| Frequency<br>MHz | Longitudinal loss<br>dB/100m<br>(dB/100ft) | Coupling Loss |         |
|------------------|--|---------------|---------|
|                  |  | 50%, dB       | 95%, dB |
| 75               | 0,55 (0,17)                                | 70 (75)       | 78 (82) |
| 150              | 0,81 (0,25)                                | 70 (75)       | 78 (82) |
| 700              | 2,00 (0,61)                                | 69 (71)       | 71 (74) |
| 800              | 2,17 (0,66)                                | 67 (71)       | 68 (73) |
| 870              | 2,29 (0,70)                                | 67 (72)       | 69 (74) |
| 900              | 2,32 (0,71)                                | 68 (72)       | 70 (75) |
| 960              | 2,43 (0,74)                                | 66 (70)       | 69 (73) |
| 1700             | 3,57 (1,09)                                | 65 (69)       | 70 (74) |
| 1800             | 3,70 (1,13)                                | 62 (66)       | 65 (70) |
| 1900             | 3,95 (1,20)                                | 62 (66)       | 65 (70) |
| 2000             | 4,15 (1,27)                                | 63 (67)       | 67 (72) |
| 2100             | 4,41 (1,34)                                | 62 (66)       | 66 (71) |
| 2200             | 4,62 (1,41)                                | 62 (66)       | 66 (71) |
| 2400             | 5,18 (1,58)                                | 63 (68)       | 67 (71) |
| 2600             | 5,80 (1,77)                                | 61 (65)       | 64 (68) |
| 2700             | 5,96 (1,82)                                | 63 (66)       | 67 (70) |

### TESTING AND ENVIRONMENTAL

#### Jacket Testing Methods

Test methods for fire behaviour of cable :  
IEC 60754-1/-2 smoke emission: halogen free, non corrosive  
IEC 61034 low smoke  
IEC 60332-1 flame retardant  
IEC 60332-3-24 fire retardant  
UL1666, ASTM E 662, NES711 and NES713

### External Document Links

### Notes

- ➔ Coupling loss as well as longitudinal attenuation of RADIAFLEX® cables are measured by the free space method according to IEC 61196-4.
- ➔ Coupling loss values are measured with a radial (below 540 MHz) or parallel (above 610 MHz) orientated dipole antenna.
- ➔ The coupling loss values given in brackets are average values of all three spatial orientations (radial, parallel and orthogonal) of dipole antenna.
- ➔ Coupling loss values are given with a tolerance of +5 dB and longitudinal loss values with a tolerance of +5%. Note: Measured values below nominal are better. They are not limited by any tolerance-range.
- ➔ In case of a conflict of operational and stop band, please contact RFS for further assistance.
- ➔ As with any radiating cable, the performance in building or tunnel environments may deviate from figures based on free space method.